

SOS

888

888

Watt

DC

USB

TYPE-C

AC

The current power of the product. It is displayed as a percentage (%).

The using time of current power.

The current total output power.

Press②for DC port function.

Press③for USB port function.

Plug Type-c cable for Type-C port function.

Press④for AC port function.

The fan is working if the temperature is over 45° .

Overload warning.

Temperature warning of Inverter. Temperature range 90°C±5°C.

DC Input

• Support AC adaptor charging.

• Support car charger charging.

• Support Solar Panel charging(12-30V).

Button: Press button to turn on and press button one more time to turn off.

What's in the box

Power Station 600W

Car Charger Cable

AC Adapter

User Manual

LCD Display

100%

888

Hours

888

Watts

100%

DC

USB

TYPE-C

AC

①

LCD Screen

DC Input

LED Flashlight

②

Car Charger Output

③

PD In/Out

④

DC Output

USB Output

AC Output

LCD Screen

LCD Screen will display charge and discharge. When you use the product, it will display the remaining power.

LCD Flashlight

Press once to get low light, press twice to get high light, press three times to get SOS, press four times to turn off the light

Important Information

Please read the user manual carefully when you use this product. You should follow all the instructions.

1. When children are using the product, please make sure they have close supervision to reduce the risks.

2. It will increase the risk of electric shock if you use non-recommend-ed products or accessories.

3. Please make sure to use the product in a ventilated environment.

4. Please keep the product in a dry and ventilated place to avoid moisture and electric shock.

5. Please remove the power plug when the product is not in use.

6. Do not expose the product to fire or excessive temperatures.It will explode if the temperature is over 130° .

7. Do not disassemble the product. It may cause fire, explosion, injury, and unpredictable risks.

















8.Do not use the product with damaged wires or plugs, or damaged output cables. It may cause an electric shock.

User Manual

RT600

Portable Power Station

Please read the user manual carefully when you use this product. You should follow all the instructions.

Specifications		
	Capacity	39Ah 14.6V 569Wh
	DC Output	13/5A*2 Total 10A
	DC Input	DC 12-30V/3.78A
	Car port Output	13V/10A
	AC Output	AC Continuous Power: 600W 240V 50Hz
	USB Output	5V/2.4A*3 QC3.0*1
	Type-C Input/Output	PD 60W
	Battery	Lithium-ion
		Pure sine Wave
	Management System	Temperature control, surge protection Short circuit protection Over-current protection Low-voltage protection
	Operating Temperature	0°C ~ 40°C
	Recharging Temperature	0°C ~ 40°C
	Weight	N.W : 5.94Kg
	Dimensions	260*173*170mm
	Certifications	FCC/CE/ETL/RoHS
	Warranty	24 Months

Support charging device


USB port: Smart phones, tablets, smart watches, digital cameras, E-readers.

13V Car charger port: Car charger, car refrigerators.


DC output: Drones, routers.

AC power: Laptops, displays, appliances, etc.


What it can power




Smart phone
Around **37** times




Tablet
Around **18** times




Laptop
Around **12** times



Drone
Around **10** times




Car refrigerators
Around **10.5** hours




Camera
Around **36** times

Charging method


Before using or storing the product,please use the wall charger to charge the unit. The LCD screen will display the current charge when the LCD screen displays 100%,it means full,this charging process is about 10 hours.



Wall Charger(72W)
About **9-10** Hours



Solar Panels (Optional)
About **7-8** Hours
(Depending on Weather)



Car charger
about **14-15** hours(12V)
7-8 hours(24V)

Instruction

How to use this product:

- Plug in your device and press the button on top of the port you are using to turn it on.
- When the port icon appears on the LCD screen, the output port will turn on for charging your device.
- The continuous AC output port can only charge/power devices that operate at less than 500 Watts. Once this limit is exceeded, the product will shut off automatically.
- The AC port output will be turned off automatically after 2 hours when being drawn under 2W power to save power.
- The DC port or car charger port will be off automatically in 8hours when being drawn under 7W power for power saving.

The USB port output will be off automatically in 8hours when being drawn under 1W power for power saving.

- If the product is not used for a long time, it should be recharged every 3 months and keep the power at 60% -80%. Please keep it in a cool and dry place.

Note

Press the AC button to turn off the output to save power when the AC power port is not in use.